






Download the "Janus Lock" App in the App Store/Google Play. After installation, this screen will appear, where you can continue your registration via e-mail. Click "**Register**" in the right bottom corner.




If you already have an account with Google, Facebook, WeChat or Apple, you can choose the appropriate registration via your already existing account.



You have chosen to register "by e-mail" (last choice), so enter your e-mail, Name and Surname, click on "Next".



Now set a password for your account and click on "**Register**". Your password must be at least 6 characters long.




You have now created an account. An activation email will be sent to the e-mail address you entered, whereby you must confirm your account's activation.




Here is a preview of the e-mail your account's activation, click on "click here" link to complete your account's activation in the Janus Lock Application.






At this stage, you can still secure access to the programme on your phone. Either by setting a PIN code, with your fingerprint, or by face recognition. If you do not want to set Janus Lock security, click "Edit later".




You can now pair the handle with the Janus Lock Application by clicking on "Pair a new lock".




You must have your phone's Bluetooth turned on.



Or it will ask you to turn Bluetooth on the Janus Lock Application itself.





Now choose a handle from the list, you want to pair and click on "**Pair**". To pair, press any button on your handle.





Your handle is now paired with the Janus Lock Application.

















You now have your handle paired with your phone. You are an administrator who grants all permissions, you have an overview of the history of who used the handle and when it was used over the last 180 days. Click "Done".





Now choose the handle you want to

configure or use.






For example, the "H03 panel" handle is selected. Click "Unlock Now" to unlock the handle.


After unlocking the handle, information regarding unlocking it appears in the Application.



Under the handle name, there is an "Unlock History" option, where you have an overview of the history of who used the handle and when over the last 180 days.




Another feature of the handle is the ability to set it to "normal handle mode". This means that no handle rules are applied in this mode. In this setting, the handle is always active from the outside (even without entering the PIN code or unlocking with your phone). Click the radio button next to the "Use as a normal handle" option.




Clicking the button next to the "Use as a normal handle" option turns "normal handle mode" setting off. This will re-enable all set rules.







If we have the handle in "normal handle mode", the handle cannot be unlocked with the phone by clicking on "Unlock Now".




Here you see all fourth options of rules that you can set for your handle. The first option is "Invite by Email or Account no". Click on "Invite".




Here you fill in the user's e-mail that you want to grant permission to. The user you are authorising must have Janus Lock installed on their phone and be registered as a user in Janus Lock. Click "Continue".



As an example, the e-mail "elektro@richterczech.cz" is entered, click on "Continue".




In this step you define the individual rules. If you do not want to set restrictive rules, click to "Anytime".




You can also set a one-time input, click "Continue".











On this screen you see a summary of the entered rule, if the rule is OK, click "Done".


If you need to edit a rule, click directly on the rule to access rule editing.




When you set more rules, it is necessary to unlock the handle for activation by the administrator. At that moment, all generated rules from the application are automatically loaded into the handle. In our case, the rule with the numeric code 4444 is waiting for activation, which you upload from the application to the handle by the administrator unlocking the handle.




If you replace the batteries or set some new rules in the Application, it is necessary for the administrator to unlock your handle to activate them. At that moment, all generated rules are automatically uploaded to your handle and are active.







The second option for setting a new rule is "Create Passcode", click on "Create".












As an example, a rule is set for entry in the time range 6:40 - 16:20, days MON, WED, FRI. If there is a rule OK, click "Continue".

Now set a PIN code with a minimum of 4 numbers and a maximum of 10 numbers. The number of PIN codes is unlimited. ATTENTION: If you select a code that has the same sequence of numbers as one of the already generated codes (e.g. 3112342 = 211235), an error message will appear and you must select another code. Click to "Create access code".




Now a code has been generated according to your settings, if there is a rule OK, click "**Done**". If you need to edit a rule, click directly on the rule to access rule editing.






The third option for setting a new rule is to set a "Generate 1-day Passcode" one-day code, click to "Generate".






January 1st, 2021. Click "Continue."




Now a code has been generated according to your settings. Either click on the "Copy" option to copy this code, or click "Done." This one-day code is not visible in the rules overview, so write it down.



The fourth option is "Register finger print". Click "**Create**".








In this step, place the desired finger on the fingerprint sensor. When the fingerprint is read correctly, number 1 lights-up.




If this message appears, you must repeat the fingerprint scan by clicking "Try again".











In this step, place the desired finger on the fingerprint sensor for a second time. When the fingerprint is read correctly, number 2 lights-up.


After your finger's third application, your fingerprint will be saved. Click "**Continue**" to go to the fingerprint rule settings.



As an example, the rule for entry is set to 9:00 - 18:00, on days Mon, Tue, Thur, Fri. Click "Continue".




Now we will save the fingerprint name (most often the username), click on "Continue".



Here we have an overview of the set rights to the given fingerprint (in our case we named the fingerprint Martin) If the rule is OK, click on "Done". If you need to edit a rule, click directly on the rule to access the rule editing.










On this screen we have information about your created account. You can also secure the application here with a PIN code, fingerprint, or face recognition.

There is also the option to switch the application to another language.



Choice "Unpair" in case you want to remove your paired handle from your account in the Janus Lock application (eg before sending the handle to another user or by sending for complaints, etc.).





18-04, dne 16.9.2020